

LIND EQUIPMENT

WORK CONFIDENTLY.

91000 PORTABLE POWER CENTRE

TEMPORARY POWER DISTRIBUTION

Features

- + Safely distribute temporary power in areas such as construction and demolition sites.
- + 125V/20A receptacles on the unit are protected by individual GFCIs with "Power On" indicators that also provide open neutral and reverse phasing protection.
- + Meets the Canadian Electrical Code requirement that all 15A and 20A receptacles on construction and demolition sites must have GFCI protection.
- + Over-current protection is provided by a full complement of circuit breakers located under an easy-access side panel.

- + 1 x 125/250V/50A Input
- + 1 x 125/250V/59A Pass-Thru for daisy-chaining units
- + 6 x 125V/20A NEMA 5-20R GFCI receptacle
- + 1 x 250V/30A NEMA L6-30R non-GFCI receptacle
- + GFCI trip level: 4-6mA
- + cULus listed
- + Dimensions: 14.5" W x 21" L x 11" H



**NEW LOWER
2012 PRICING!**

Part Numbers

- + 91000 - Main unit
- + 91006 - Canadian approved input power cord, 50', 6/3-8/1 AWG
- + 91007 - Canadian approved input power cord, 100', 6/3-8/1 AWG



For more information about our other lines of portable electrical equipment for the toughest workplaces:

www.lindequipment.net | info@lindequipment.net | T: 877.475.LIND